















Compatible with

- 40Vmax XGT Li-lon battery
- 18V LXT Li-lon battery
- AC (through AC adapter)









AC









Max air flow volume

Max air speed*

Compatible with 40Vmax / 18V Li-Ion battery /AC



XGT battery and LXT battery can be installed simultaneously.

Manual angle adjustment of fan head



90° up/45° down with a locking knob

Stepless air flow volume setting



Dial-style air flow volume adjustment (38 - 120m³/min)

Can be mounted onto **MAKPAC** cart



Portability can be enhanced by mounting the appliance onto MAKPAC cart.

Automatic oscillation



Automatic oscillation angle adjustment: 60°, 90°, 120° left/right

Accessory case



Located on the front of the appliance for storing AC adapter, etc.

Continuous use (approx)

on a full battery charge [at Max air speed]

Battery	Without oscillation	With oscillation
BL1860B	90 min	85 min
BL4040	115 min	110 min
BL4080F	230 min	220 min



Charging Time

40 Vinax	DC40RA	DC40RC	18V	Fast Charging DC18RC	DC18SD
BL4020 2.0Ah	22 min	30 min	BL1815N 1.5Ah	15 min	30 min
BL4025 2.5Ah	28 min	38 min	BL1820B 2.0Ah	24 min	45 min
BL4040 4.0Ah	45 min	67 min	BL1830B 3.0Ah	22 min	60 min
BL4050F 5.0Ah	50 min	85 min	BL1840B 4.0Ah	36 min	90 min
BL4080F 8.0Ah	76 min	170 min	BL1850B 5.0Ah	45 min	110 min
,			BL1860B 6.0Ah	55 min	130 min

not covered by EPTA-Procedure

Items of standard equipment and specifications may vary by country or area.

Cordless Fan

CF003G 40Vmax / 18V / AC



Air velocity Air flow Fan diameter Fan head angle adjustment Automatic oscillation

Continuous use (min.) w/o oscillation Continuous use (min.)

96-300 m/min 38-120 m³/min 450 mm (17-3/4") Up: 90° / Down: 45° Left: 90° / Right: 90° Left: 60, 90, 120° Right: 60, 90, 120° w/BL4040: 115 / w/BL4080F: 230 /

w/BL1860B: 90 w/BL4040: 110 / w/BL4080F: 220 /

Standard Equipment: AC adaptor

Makita Corporation