

Cordless Brad Nailer DBN500



Provides less reaction force and "air nailer like" shot feeling to the operator.



Higher durability

Makita driving mechanism* provides longer service life.

*The compressed air (generated by piston action linked with DC motor) moves driving guide.



More work amount enabling to shoot 1,000 nails on a single battery BL1830 charge LED job light tuns on when double trigger is pulled.

Power by 18V Li-ion battery



BL1850: 18V 5.0Ah BL1840: 18V 4.0Ah BI 1830: 18V 3.0Ah





BL1815N: 18V 1.5Ah

Rocker switch to select Sequential mode / Bump fire mode

When you set the switch to the Bump fire mode, 1 and 2 are automatically selectable.

- 1. Nails can be shot one after the other continuously first by pulling Trigger then by bumping Contact arm against workpiece with the Trigger pulled.
- 2. One nail can be shot at a time first by pressing Contact arm on workpiece then by pulling Trigger (worked as Single fire mode)

LED warning lamp for Battery capacity

completely used up.

Blinking: Battery power has been almost used up. Solid: Battery power has been



Easy-to-see slim nose tip

allows quick and easy access to a desired fastening point.



narrow spots.

Driving depth adjustment



DC18RC



DC18SF

Charging time (3.0Ah) 1 to 2 batteries: 60minutes 3 to 4 batteries: 120minutes



DC18SD Charging time (3.0Ah) 60minutes









Sequential or Bump-fire



Cordless Brad Nailer | DBN500Z (Skin Only)

Capacity Lenath: 15-50mm (5/8-2") Gauge :18Ga 110pcs

Magazine capacity Dimensions BL1850: 294x97x318mm (LxWxH) (11-5/8"x3-13/16"x12-1/2") BL1850: 3.5kg (7.7lbs)

Standard Equipment: Safety Goggles, Nose Adapter, Hex Wrench

weight according to EPTA-Procedure 01/2003 Items of standard equipment and specifications may vary by country or area.

